

QSSM-3114 (HDMI 2.0)

QSSP-3114 (4K DP)

4 Ports True 4K KVM Switch with Seamless Switch, Serial Control, Keypad In, USB 3.2 Gen 1



QSSP-3114



QSSM-3114

Features

- Allows 4 Computers Sharing 1 Set of KVM Console
- Most Popular Resolution Supported** Up to 4K@60Hz, & 16:9 / 21:9 / 32:9 Aspect Ratios
- Seamless Switching** Grants the Best Productivity
- HDCP 2.2 / 1.4 Compliance** Ensures Uninterrupted Video Playback
- HDR10 Compliance** Gives the Best Visual Experience
- Continuous & Unified** Video Output Minimizes the Start-Up Procedure
- Flexible Control Methods Suits Variable Scenarios :
 - Push Button - Keyboard Hotkey
 - Serial Control - Keypad Control
- Serial Control** Facilitates Industrial Control Purposes (8-Bands Baud Rate Selectable)
- Keypad In** Supports Wired & Wireless USB Keypad, and Allows Controlling the KVM Remotely
- DP Model Equipped with an Extra HDMI Output (QSSP-3114)
- Output Scaling Function** Facilitates Connection to Projector / KVM Extender / Video Extender

Connection Pattern



Specification

Model Number		QSSM-3114 & QSSP-3114	
MAX. Resolution (4K@60Hz, 4:4:4)		3840x2160, 2560x1440, 1920x1080	
		3840x1600, 3440x1440, 2560x1080	
		3840x1080, 2048x2048, 1536x2048	
Interfaces		PC Side	Console Side
Video Switching	QSSM-3114	HDMI 2.0 x 4 (In)	HDMI 2.0 x 1 (Out)
	QSSP-3114	4K DP x 4 (In)	HDMI 2.0 x 1 (Out) 4K DP x 1 (Out)*
USB 3.2 Switching (5Gbps)		USB 3.2-B x 4	USB 3.2-A x 1 USB HID-A x 3
Audio Switching		SPK x 4 (In)	SPK x 1 (Out)
Control Methods		Hotkey Control, Serial Control Keypad In, Front Push Buttons	
Video Output Scaling		Auto, User Define 4K@30Hz, 1080P	
Seamless Switching		Zero Latency	
Serial Control		RJ-11 x 1 (19200bps) (8-Selections, 9600~115200bps) USB-C x 1	
Push Buttons		Port-Select x 4, Function x 4	
Hot Plug-and-Play		Yes	